

# UniMRCP MRCP connector for Asterisk

## About

### uniMRCP

Cupertino, CA, USA

Website: <https://www.unimrcp.org/>

## Definition

The Voximal can connect to a ASR engine using MRCP. The Media Resource Control Protocol (MRCP) is a network protocol based on the client/server model. MRCP allows client applications to control media service resources residing in servers. The first version of the protocol was published as an informational document, whereas its successor, MRCPv2, is currently a proposed standard.

UniMRCP is an open source cross-platform implementation of the MRCP client and server in the C/C++ language distributed under the terms of the Apache License 2.0. The implementation encapsulates SIP, RTSP, SDP, MRCPv2, RTP/RTCP stacks and provides integrators with an MRCP version consistent API.

The UniMCRP offers a module for Asterisk (from Asterisk 1.4 to 14), we had done many modifications for a better integration with the VoiceXML interpreter.

[uniMRCP Voximal Github](#)

## Installation

uniMRCP module is integrated in the Voxibot Suite.

If you need to install on the Asterisk, please contact our support team.

## Configuration

This link provides quick references to the documents which guide you through installation and configuration steps as well as introduce the project architecture.

Documentation : [Get Started!](#)

## Extended configuration

### Multiple ASR engines configuration

The module allows now to configure more than engine. In the section [general], we can set several profiles :

```
unimrcp-profile = uni1,loq1,ves1
```

The engine declare more than one speech resource, and define then with : unimrcp:[profilename].

You can access then from the VoiceXML module configuration with :

```
speechprovider=unimrcp:uni1
```

Example of configuration file :

```
;  
; UniMRCP ASR and TTS connector Configuration  
;  
[general]  
;unimrcp-profile = loq1      ; Loquendo MRCPv2 Server  
;unimrcp-profile = ves1     ; UniMRCP MRCPv1 Server  
;unimrcp-profile = lv2      ; LumenVox MRCPv2 Server  
;unimrcp-profile = lv1      ; LumenVox MRCPv1 Server  
;unimrcp-profile = nss2     ; Nuance MRCPv2 Server  
;unimrcp-profile = nss1     ; Nuance MRCPv1 Server  
unimrcp-profile = uni1,loq1,ves1      ; 3 MRCPv1 Servers  
  
log-level=DEBUG ;EMERGENCY  
log-output=3 ;1 console, 2 file, 3 both  
cancelifqueue=false  
returnnlsmml=true  
vendorspecificparameters=no  
setparams=true  
removeswi=yes  
startinputtimers=false  
;max=2  
dtmfstopspeech=no  
  
[grammars]  
;grammar-name = path-to-grammar-file  
  
[mrcpv2-properties]  
Start-Input-Timers = TRUE  
Recognition-Timeout = 20000  
No-Input-Timeout = 3000  
Speech-Language = es-ES ;en-US
```

```
[mrcpv1-properties]
Recognizer-Start-Timers = TRUE
Recognition-Timeout = 20000
No-Input-Timeout = 30000
Speech-Language = es-ES ;en-US
```

From:

<https://wiki.voximal.com/> - **Voximal documentation**

Permanent link:

<https://wiki.voximal.com/doku.php?id=asrproviders:unimrcp&rev=1485339482>

Last update: **2017/01/25 10:18**

